

Quick guide SRT326i

Personal alarm

SRT3260500A19_QG_EN_STD



On/off

Press and hold the on/off button for 5 seconds.

The device will start vibrating and initiate the turning on/off sequence.



Sending an alarm

Press and hold the alarm button until the device vibrates.

The device will emit a second, shorter vibration when the alarm has been sent.



Acoustic warning

If the SIM card is out of place the device will emit an audible signal. Shut the device off, extract and reinsert the SIM card and turn the device on again.

Charging port →

SIM card →



On/Off button



Call button



Enable/disable Timer alarm



Enable/disable Man down alarm

Status LEDs

GSM status

Blinking (red)

Searching for GSM network

Blinking (green) slowly

GSM network found

Blinking (green) quickly

Call in progress.

No light

The device is either turned off or in idle mode.



MD status

No light

Man down function is disabled.

Blinking (yellow)

Man down function is enabled



TMR/RF status

Blinking (green)

Device is in contact with RF tag.

No light

No contact with any RF tags. Timer alarm is disabled.

Blinking (yellow)

Timer alarm is enabled.

Blinking (green/yellow)

The device is in contact with RF tag. Timer alarm is enabled.



Charge level (PWR) (charger disconnected)

Blinking three times every 15 seconds

The device is turned on and is signaling the battery level with the three blinks:

Very good

● green ● green ● green

Good

● green ● green ● red

Low

● green ● red ● red

Critical

● red ● red ● red

Blinking interchanging green and red

The device is turning off.



Charging

(Desktop charger)

Place the unit in the desktop charger

Charging (USB)

Lift the rubber flap on the side of the device and insert the charger cable into the mini usb connector.



Charge level (PWR) (charger connected)

Blinking every other second (green)

The device is turned on and charging.

Blinking every other second (red)

The device is turned off and charging.

Solid light (green)

The device is turned on and fully charged.

Solid light (red)

The device is turned off and fully charged.

Blinking interchanging green and red

The device is turning off.

Charging times

Before using your alarm device the first time, or whenever the battery is fully discharged, it should be charged for at least 4 hours. The device should be charged every day.