

Quick guide SRT306i

Personal alarm

SRT3060300A19_QG_EN_STD

On/off
press and hold the on/off button for 5 seconds. The device will start vibrating and initiate the turning on/off sequence.



Sending an alarm
Press and hold the alarm button until the device vibrates. The device will emit a second, shorter vibration when the alarm has been sent.



Acoustic warning
If the SIM card is out of place the device will emit an audible signal. Shut the device off, extract and reinsert the SIM card and turn the device on again.



-  On/Off button
-  Call button
-  Enable/disable Timer alarm
-  Enable/disable Man down alarm

Status LEDs

GSM status

Blinking (red)

Searching for GSM network

Blinking (green) slowly

GSM network found

Blinking (green) quickly

Call in progress.

No light

The device is either turned off or in idle mode.



MD/GPS status

Blinking (green)

The device have a current GPS position.

No light

GPS is either turned off, is in idle mode or have no current position.

Man down is disabled.


Blinking (yellow)

Man down is enabled.

Blinking (grön/gul)

The device have a current GPS position.

Man down is enabled.



TMR/RF status

Blinking (green)

Device is in contact with RF tag.

No light

No contact with any RF tags. Timer alarm is disabled.

Blinking (yellow)

Timer alarm is enabled.

Blinking (green/yellow)

The device is in contact with RF tag. Time alarm is enabled.

Charge level (PWR) (charger disconnected)

Blinking three times every 15 seconds

The device is turned on and is signaling charge level with the three blinks. Very good

● green ● green ● green

Good

● green ● green ● red

Low

● green ● red ● red

Critical

● red ● red ● red

Blinking interchanging green and red

The device is turning off.

Charging

(Desktop charger)

Place the unit in the desktop charger

Charging (USB)

Lift the rubber flap on the side of the device and insert the charger cable into the mini usb connector.



Charge level (PWR) (charger connected)

Blinking every other second (green)

The device is turned on and

Blinking every other second (red)

The device is turned off and charging.

Solid light (green)

The device is turned on and fully charged.

Solid light (red)

The device is turned off and fully charged.

Blinking interchanging green and red

The device is turning off.

Charging times

Before using your alarm device the first time it should be charged for 4 hours. Whenever the battery is fully discharged it should be charged for at least 4 hours.

The device should be charged every day.