



SRT3300100A08\_PB\_EN\_STD

# SRT330

SRT330 is a GSM alarm receiver that quickly and effectively indicates when an alarm is triggered.

## Alarm

SRT330 is an alarm receiver that can be used together with all SRT alarm products. When SRT330 receives an alarm this is indicated through auditory and visual warning signals.

## Display

When an alarm is received the display shows the sending number. It is also possible to associate the sender's number with an arbitrary text string, such as a co-workers name, place or vehicle, which is then displayed when an alarm is received.

## Emergency service center

Your SRT alarm device can be programmed to send alerts to multiple recipients. That means an alarm unit can send alerts to both an emergency service center and SRT330 when an alarm is triggered.

## Battery

With a powerful internal battery of 6.6 Ah SRT330 can run without an external power supply for over 3 days.

## Alarm relaying

SRT330 can relay alarms, in the form of an SMS, to as many as 100 recipients.

- Developed in Sweden
- GSM
- Warning light
- Alarm siren
- Reset / Test button
- Alarm button
- Display
- Internal battery 6.6 Ah
- Relay on alarm reception
- Can send low battery alarms to preset numbers
- Size 190x130x80 mm
- Weight: 600g

## Accessories

Wall Charger.

Learn more about SRT330 on our website, [www.srt.se](http://www.srt.se).